AD-A072 202   MASSACHUSETTS INST OF TECH LEXINGTON LINCOLN LAB   F/G 12/1
               ASYMPTOTICALLY OPTIMAL DETECTOR OF MEMORY P FOR K-DEPENDENT RAN--ETC(U)
               MAY 79   L K JONES   F19628-78-C-0002
UNCLASSIFIED   TN-1979-42   ESD-TR-79-83   NL

| OF |

AD
A072 202

END
DATE
FILMED

9-79

DDC

MICROCOPY RESOLUTION TEST CHART
NATIONAL BUREAU OF STANDARDS 1963 A

MASSACHUSETTS INSTITUTE OF TECHNOLOGY

LINCOLN LABORATORY

⑥ ASYMPTOTICALLY OPTIMAL DETECTOR OF MEMORY p
FOR k-DEPENDENT RANDOM SIGNALS.

⑩ K. JONES

Group 92

Lee

⑭ TN-1979-42

⑨ TECHNICAL NOTE 1979-42

⑪ 8 MAY 1979

⑫ 14 P.

⑮ F19628-78-C-0002

⑯ 627A

Approved for public release; distribution unlimited.

⑱ ESD ⑲ TR-79-83

D D C
RECEIVED
AUG 6 1979
D

LEXINGTON   MASSACHUSETTS

207 650

79 08 2 001

Abstract

This note describes a general method for discriminating
between two k-dependent stationary discrete random vari-
ables using marginal statistics and their first order
correlations.

Asymptotically Optimal Detector of Memory p
for k - dependent Random Signals

Lee K. Jones

A stationary discrete time series $\{X_i\}_{i=1}^{\infty}$ is said to be k-dependent if for every integer m, $\{X\}_{i \leq m}$ is independent of $\{X_i\}_{i>k+m}$. Suppose $\{X_i^1\}$ and $\{X_i^2\}$ are two stationary k-dependent random signals occurring with prior probabilities α and $1-\alpha$ respectively. If n pulses of a random signal are observed (n large compared to k) how do we decide whether we observed $\{X_i^1\}_{i=1}^n$ or $\{X_i^2\}_{i=1}^n$?

A detector L of memory p is given by a function $L(X) = L(x_1, x_2, \ldots, x_n) = \sum_{i=p+1}^{n} g_i(x_i, x_{i-1}, \ldots, x_{i-p})$ and a set $A^{(1)}$ of real numbers such that:

for $L(X) \in A$ we choose class 1

for $L(X) \in A^C$ we choose class 2

In view of the stationarity we need only consider (for n large compared to p) detectors for which $g_i = g$ for all i.

Suppose both $\{X_i^1\}$ and $\{X_i^2\}$ are bounded with known (or estimates of) statistical properties (correlations, moments, etc.). In this note we use a straightforward extension of the method of minimal marginal moment variance[2] to determine the g which

---

(1)   For the cases we shall consider, A is the union of one or two intervals.

(2)   Introduced in [2] to solve for the case p=0, k=0.

minimizes the probability of error. This solves the problem addressed in [1] ($p=0$, $x_i^1 = \theta + n_i$, $x_i^2 = n_i$, n_i k-dependent).

Solution: Let 1, h_1, h_2, ... be a complete set of continuous functions on R^{p+1}. For $g_q = \sum_1^q a_j h_j$ we find the coefficients a_j which minimize the probability of error. The constant function 1 need not be present in this expansion since it trivially has the same statistical properties under both hypotheses. As q becomes large the error probability using g_q converges to the error probability for the optimal g.

Consider $L(X) = \sum_{i=p+1}^{n} g_q (x_i, x_{i-1}, \ldots, x_{i-p})$. It is a sum of bounded k+p - dependent random variables. Hence L is asymptotically normal under each hypothesis. The set A will in general be described by 2 thresholds. (If a single threshold detector is desired the following analysis remains the same.)

Let $\mathcal{E}(a_j)$ = probability of error = $\int_{-\infty}^{+\infty} \min \{\alpha p_1, (1-\alpha) p_2\}$ dx where p_i is the probability density of L under hypothesis i. By normality p_1 and p_2 are characterized by their means and variances. We now restrict a_j such that $E_2 L(X) - E_1 L(X) = 1$. $\mathcal{E}$ is then a function of the variances of L under each hypothesis: $\mathcal{E} = \mathcal{E}(v_1(a_j), v_2(a_j))$. Taking the gradient wrt a_j and using λ as a Lagrange multiplier we have:

$$\frac{\partial \mathcal{E}}{\partial v_1} \nabla v_1 + \frac{\partial \mathcal{E}}{\partial v_2} \nabla v_2 - \lambda(\nabla(E_2 L - E_1 L)) = 0 \tag{1}$$

The partials $\frac{\partial \mathcal{E}}{\partial v_i}$ may be negative (even for a single threshold detector) but are not both zero. It is easy to see that a solution of (1) is a critical point of the objective function $\beta v_1 + (1 - |\beta|)v_2 - \Phi(E_2L - E_1L - 1)$ where Φ is a Lagrange multiplier and $-1 \leq \beta \leq +1$. This critical point may be determined for various values of β and the β corresponding to minimum probability of error determined from normal tables.

We now proceed with the calculations. Let

$$h_j^i = h_j(x_i, x_{i-1}, \ldots, x_{i-p})$$

$$\rho_{ijs}^\ell = E_i \left[(h_j^{\,1} - E_i h_j^{\,1}) (h_s^{1+\ell} - E_i h_s^{1+\ell}) \right]$$

By differentiating the above objective function wrt a_j and setting the result equal to zero we obtain:

$$\left[\beta A_1 + (1-|\beta|)A_2 \right] \vec{a} = \frac{\Phi}{2} (n-p) \vec{m} \tag{2}$$

where $m_j = E_2 h_j^1 - E_1 h_j^1$

and $(A_i)_{js} = (n-p)\rho_{ijs}^0 + \displaystyle\sum_{\ell=1}^{k+p} (n-p-\ell) (\rho_{ijs}^\ell + \rho_{isj}^\ell)$

Solving equation (2) -

$$\vec{a} = \Phi \left(\frac{n-p}{2}\right) \left[\beta A_1 + (1-|\beta|)A_2 \right]^{-1} \vec{m} = \Phi \vec{g}_\beta$$

Then

$$\Phi = \left(\sum_{j=1}^{q} g_{\beta j} \, m_j \right)^{-1} \quad \text{from the condition} \quad E_2L - E_1L = 1.$$

3

v_1 and v_2 may now be calculated and the error (as a function of β) determined. The β corresponding to minimum error is then obtained by a one-parameter minimization. The preceding method will yield an optimal detector whenever the p_i occurring in the expression for $\mathcal{E}(a_i)$ depend only on the means and variances of L. We need only estimate the error as a function of β from the performance of L on sample data.

References

[1] H. V. Poor and J. B. Thomas, "Time Detection of a Constant Signal in m-Dependent Noise," IEEE Trans. Inform. Theory IT-25, Pages 54-61, (1979).

[2] On Optimal Discriminants between two Classes of Random Variables in Terms of the Moments of their Distributions, submitted to SIAM Journal of Appl. Math.

REPORT DOCUMENTATION PAGE		READ INSTRUCTIONS BEFORE COMPLETING FORM
1. REPORT NUMBER ESD-TR-79-83	2. GOVT ACCESSION NO.	3. RECIPIENT'S CATALOG NUMBER
4. TITLE (and Subtitle) Asymptotically Optimal Detector of Memory p for k-Dependent Random Signals		5. TYPE OF REPORT & PERIOD COVERED Technical Note
		6. PERFORMING ORG. REPORT NUMBER Technical Note 1979-42
7. AUTHOR(s) Lee K. Jones		8. CONTRACT OR GRANT NUMBER(s) F19628-78-C-0002
9. PERFORMING ORGANIZATION NAME AND ADDRESS Lincoln Laboratory, M.I.T. P.O. Box 73 Lexington, MA 02173		10. PROGRAM ELEMENT, PROJECT, TASK AREA & WORK UNIT NUMBERS Program Element No. 63311F Project No. 627A
11. CONTROLLING OFFICE NAME AND ADDRESS Air Force Systems Command, USAF Andrews AFB Washington, DC 20331		12. REPORT DATE 8 May 1979
		13. NUMBER OF PAGES 10
14. MONITORING AGENCY NAME & ADDRESS (if different from Controlling Office) Electronic Systems Division Hanscom AFB Bedford, MA 01731		15. SECURITY CLASS. (of this report) Unclassified
		15a. DECLASSIFICATION DOWNGRADING SCHEDULE

16. DISTRIBUTION STATEMENT (of this Report)

Approved for public release; distribution unlimited.

17. DISTRIBUTION STATEMENT (of the abstract entered in Block 20, if different from Report)

18. SUPPLEMENTARY NOTES

None

19. KEY WORDS (Continue on reverse side if necessary and identify by block number)

20. ABSTRACT (Continue on reverse side if necessary and identify by block number)

This note describes a general method for discriminating between two
k-dependent stationary discrete random variables using marginal statistics
and their first order correlations.

DD FORM 1473 EDITION OF 1 NOV 65 IS OBSOLETE
1 JAN 73